ATS-US

GROWATT (ATS-US) Auto Transfer Switch and US Split Phase Transformer

- ATS-US comes with built-in transformer
- ATS 5000T -US has a maximum sum of L1-N and L2-N simultaneous output is 5000VA
- ATS 11400T -US has a maximum sum of L1-N and L2-N simultaneous output is 11400VA



POWER-ING TOMO-RROW

GROWATT

www.ginverter.com

Product model	ATS 5000T- US	ATS 11400T-US
Input Data		
EPS		
Normal Voltage	240V	
Normal Frequency	50/60Hz	
Max. Power	5000VA	11400VA
Max. Current	21A@240Vac	48A@240Vac
AC Grid		
Normal Voltage	240V	
Normal Frequency	50/60Hz	
Max. Power	5000VA	11400VA
Max. Current	21A@240Vac	48A@240Vac
Output Data		
Split Phase Data		
Rated Power(L-L)	5000VA	11400VA
Rated balanced power(L-N)	5000VA	11400VA
Rated unbalanced power(L-N)	3000W	
Output voltage	120/240Vac	
Max continued current(L-L)	21A@240Vac	48A@240Vac
Max continued current(L-N)	25A@120Vac	25A@120Vac
General Data		
Cooling	Natural Convection	
Ingress Protection	NEMA 4X(IP65)	
Installation	Wall Mountable	
Operating Temperature Range	-25~+55°C(-13 ~ +131°F)	
Weight	15.6kg/34.3lb	
Dimensions（W/H/D）	18.9/10.8/4.1in(480/275/105mm)	
Warranty	10 Years	
	UL1741:2018 CSA C22.2 NO 107.1:2016	

The rated power of secondary side L1-N and L2-N could up to 5kVA respectively, and the power difference between the two split phases can not exceed 3kW.

GROWATT USA INC. Address: 9227 Reseda Blvd. #435 Northridge, CA 91324. Sales Hotline : 818 800 9455 Service Hotline : 1866 686 0298
Email: usa@ginverter.com